

# Power Stream™ 4

## SPECIFICATIONS & FEATURES

CHAUVET®



### AT A GLANCE:

#### Key Features:

- Allows for easily power splitting with powerCON connections, works in same theory as a conventional power strip.
- Provides 1 input jack, 4 output jacks and 1 power through jack to continue running a main "feeder" line.
- Creates neater and cleaner cable runs, especially when using fixtures with no power linking capability.
- Durable steel construction stands up to the rigors of the road.
- 20 A inline circuit breaker provides a level of overdrive protection.
- Does NOT multiply current, power in = power out to a max of 20 A.
- Saves time running cables in a touring environment

#### About this Fixture:

PowerStream™ 4 is an ingenious splitter for powerCON® connections. Placed into the main power feed, it taps into up to four connections out to fixtures, allowing users to pre-rig a truss and limit the need for additional cables.

### DETAILED SPECIFICATIONS:

#### Electrical

AC Voltage Range: 100~240V, 50/60Hz

Circuit Breaker: 20 A

#### Physical

Dimensions: 8.4 x 2.4 x 3 in (214 x 62 x 75 mm)

Weight: 1.7 lbs (0.8 kg)

Housing Material: Steel

Power Input Connection: Neutrik® powerCON®

Power Output Connection: Neutrik® powerCON®

Power Output Quantity: 4 + 1 power through

#### Listings

Certification: CE

Environment: IP20, dry location

#### Optional Accessories

Control: N/A

Mounting: N/A

Cablings: powerCON® Extension (18 in, 5/10/25/50 ft)

[www.chauvetlighting.com](http://www.chauvetlighting.com)  
[www.chauvetlighting.co.uk](http://www.chauvetlighting.co.uk)

CHAUVET®