

Art No. SH0001

∑Central

The central unit for monitoring and controlling up to 16 Σ Casa products.

Features:

- Access, manage and schedule multiple ∑Casa devices from remote site
- Multiple control up to 16 devices simultaneously
- Notification will be sent to smart phone or tablet when events occur
- Exclusive ∑Link feature enable various combination of conditions to activate your smart life



Free APP for Android and iOS. Search for "Sigma Casa"



Control and Monitor your home automation system anywhere!







* The specifications and pictures are subject to change without notice. *All trade names referenced are the registered namework of their respective owners.

Made in Taiwan



Art No. SH0001

∑Central

Specification:

Dhugha ath, Cara a'f' anti an	V/4 O
Bluetooth Specification	V4.0
Power Supply	DC 5V/1A (Micro USB)
WiFi Antenna	Built-in chip antenna
Bluetooth Antenna	Rod antenna (external)
Communication	WiFi + Bluetooth 4.0
Transmission Range	100m for open space, 25m for mixed space
WiFi Security Supported	OPEN, WEP, WPA, WPA2, WPA+WPA2
WiFi Encryption Supported	CCMP/AES, TKIP,TKIP+CCMP/AES
WiFi Authentication Supported	PSK
Operating Temperature	$0^{\circ}C \sim 40^{\circ}C$
Dimension	70mm x 70mm x 22,6mm
Weight	ббд

System Requirements:

- iOS 8.0 and above with Bluetooth 4.0
- Android 4.3 and above on Bluetooth 4.0 ready devices

Package Contents:

- 1 x ∑Central
- 1 x 5V Power Adapter
- 1 x Micro-USB Cable
- 1 x 2.4GHz SMA Antenna
- 1 x User Manual

Packaging Information:

- Packing Dimension: mm
- Packing Weight: kg
- Carton Dimension: mm
- Carton Q'ty: pcs
- Carton Weight: kg

1 ΣCASA





* The specifications and pictures are subject to change without notice. *All trade names referenced are the registered namework of their respective owners.

Made in Taiwan

